

HILBERT TRANSFORM OF IRREGULAR WAVE PACKET SYSTEM FOR $L^2(\mathbb{R})$

A.K. SAH AND L.K. VASHISHT[†]

Date of Receiving : May 05, 2014

Date of Revision : May 24, 2014

Date of Acceptance : June 20, 2014

Abstract. Let $\{D_{a_j} T_{b_k} E_{c_m} \psi\}_{j,k,m \in \mathbb{Z}}$ be an irregular wave packet system and let H be the Hilbert transform on $L^2(\mathbb{R})$. In this paper we give necessary and sufficient conditions for the system $\{D_{a_j} T_{b_k} E_{c_m} H\psi\}_{j,k,m \in \mathbb{Z}}$ to be a frame for $L^2(\mathbb{R})$.

1. Introduction and Preliminaries

A sequence $\{f_k\}$ in a separable Hilbert space \mathcal{H} with inner product $\langle \cdot, \cdot \rangle$ is called a *frame* (or *Hilbert frame*) for \mathcal{H} , if there exists finite positive constants A and B such that

$$A\|f\|^2 \leq \|\langle f, f_k \rangle\|_{\ell^2}^2 \leq B\|f\|^2, \text{ for all } f \in \mathcal{H}. \quad (1.1)$$

The positive constants A and B are called *lower* and *upper* bounds of the frame, respectively. The inequality (1.1) is called the *frame inequality* of the frame. If upper inequality in (1.1) holds, then $\{f_k\}$ is called a *Bessel sequence*. The operator $T : \ell^2 \rightarrow \mathcal{H}$ given by

$$T(\{c_k\}) = \sum_{k=1}^{\infty} c_k f_k, \quad \{c_k\} \in \ell^2,$$

is called the *synthesis operator* or the *pre-frame operator* of the frame. The adjoint operator $T^* : \mathcal{H} \rightarrow \ell^2$ of T is called the *analysis operator* and is given by

$$T^* : f \rightarrow \{\langle f, f_k \rangle\}, \quad f \in \mathcal{H}.$$

2010 *Mathematics Subject Classification.* 42C15, 42C30.

Key words and phrases. Wave packets frames, Wave packets Bessel sequence, Hilbert transforms.

The authors would like to thank the referee for careful reading of the paper. The second author is partly supported by R & D Doctoral Research Programme, University of Delhi, Delhi. Grant No. DRCH/R& D/2013-14/4155.

Communicated by: Suman Panwar

[†]Corresponding author.